



The AccelTex inline RF connector adapter converts an existing style or gender connector to easily mate with another style or gender. These adapters are built to minimize insertion loss and are an easy and efficient way to change styles and genders within an RF system.

Part Number: ATS-RPSMAJ-RPTNCJ

> ELECTRICAL SPECIFICATIONS

Impedance: 50Ω
Frequency Range: DC-5.85 GHz
VSWR: ≤1.3
Insertion Loss: ≤0.2dB

Center Conductor Contact Resistance: ≤ 10mΩ
Outer Conductor Contact Resistance: ≤ 2.5mΩ
Dielectric Withstand: 1000V RMS
Insulation Resistance: ≥ 5000MΩ

> MECHANICAL SPECIFICATIONS

Connector 1 Style: RPSMA Jack
Connector 2 Style: RPTNC Jack
Adapter Shape: Straight
Mating: 1/4-36UNS-2A and 7/16-28UNEF-2A
Durability: ≥ 500 Cycles

Body: Nickel Plated Brass
Insulator: Teflon
Contact Pin: Gold Plated Brass

> ENVIRONMENTAL SPECIFICATIONS

Operating Temperature: -67 to 311°F (-55 to 155°C)

> STANDARDS, TESTING AND CERTIFICATIONS

IEC 60169-15 and IEC 60169 –17
ROHS 2011/65/EU Compliant

> WARRANTY

1 Year Limited Warranty